

100V Volume Control without Relay (6/24/36/50 Watt)




Features:

- ✓ PA (Public address) system use volume control.
- ✓ Background music system use attenuator.
- ✓ The public address system volume controller is used to adjust the loudspeaker output in the room.
- ✓ The PA system volume controller is used to keep same output level for one same speaker line, because the end the speaker line signal loss is rather big, so its outputs is less, thus volume controller is added to the front of the line to lower the speaker output so as to keep the similar ambient output level for the all of the speaker in the same line.
- ✓ High level white UV-protected ABS material to integrate together with the white wall and architecture design.
- ✓ Built-in transformer to control the PA 100V line loudspeakers.
- ✓ With 10 levels of volume attenuator and one position of off.
- ✓ Wall plate and front panel are separated fixed together.
- ✓ Surface wall mount or in-wall mounting box shall be purchased separated.


SPECIFICATION:

Model	VC006H	VC024H	VC036H	VC050H
Description	100V Volume Controller			
Rated Output	6W	24W	36W	50W
Transformer	No	Yes	Yes	Yes
Line Input	100V or 70V			
Volume Step	10 steps			
Attenuation Per Step	3dB			
Total Attenuation	33dB			
Material	UV-protected ABS			
Finish	White			
Mounting Way	Surface mount or in-wall mount			
Dimension	80(W)*80(D)*48(H)mm			

Rear View:



Wiring Diagram:



The information provided in this data brochure is correct at the time of printing. All changes or modifications, may then be technical or other, or changes in the availability of products are expressly reserved. No liability will be assumed for printing mistakes and errors. ©isoelectra Far East Pte Ltd.

No. 8 Commonwealth Lane #02-04 Singapore 149555, Tel: +65 6272 2371 Fax: +65 6278 9019, Email: enquiry@isoelectra.com.sg, Website: www.isoelectra.com.sg