



100V Volume Control with Optional Relay (6/30/60/120 Watt)**Features:**

- ✓ PA (Public address) system use 100V volume controller.
- ✓ Background music system use 100 volt attenuator.
- ✓ Classic range volume controller for cost-effective system use.
- ✓ The volume controller is used to adjust the loudspeaker output in the room.
- ✓ The volume controller is used to keep same output level for one same speaker line, because the end the speaker line signal loss is rather big, so its outputs is less, thus volume controller is added to the front of the line to lower the speaker output so as to keep the similar ambient output level for the all of the speaker in the same line.
- ✓ High level white UV-protected ABS material to integrate together with the white wall and architecture design.
- ✓ Built-in transformer to control the PA 100V or 70V line loudspeakers.
- ✓ With 10 levels of volume attenuator and one position of off.
- ✓ Surface wall mount or in-wall mounting box shall be purchased separated.
- ✓ 24V relay are optional to buy

SPECIFICATION:

Model	VC006C	VC030C	VC060C	VC120C
Description	100V Volume Controller (with optional 24VDC Relay)			
Rated Output	6W	30W	60W	120W
Line Input	100V or 70V			
Volume Step	11 steps			
Attenuation Per Step	3dB			
Total Attenuation	33dB			
Material	UV-protected ABS			
Finish	White			
Mounting Way	Surface mount or in-wall mount			
Depth	50mm	60mm	60mm	60mm
Plate Dimension	86(W)×86(D)mm			

Dimension And Side View:

Wiring Diagram:


The information provided in this data brochure is correct at the time of printing. All changes or modifications, may then be technical or other, or changes in the availability of products are expressly reserved. No liability will be assumed for printing mistakes and errors. ©isoelectra Far East Pte Ltd.

No. 8 Commonwealth Lane #02-04 Singapore 149555, Tel: +65 6272 2371 Fax: +65 6278 9019, Email: enquiry@isoelectra.com.sg, Website: www.isoelectra.com.sg